

DSL-2750U Internet Setup Guide

Connect with cable to the DSL-2750U

Once connected, open your internet browser (i.e. Internet Explorer, Google Chrome, Mozilla Firefox)

In the URL bar, type <http://192.168.1.1> and press enter

Username: admin

Password: admin



LOGIN

Welcome to Web Management

Username :

Password :

Remember my login info on this computer



After entering the username/password, click Login

Once logged in, navigate to Setup -> Internet Setup

If there is a profile on this page, tick it's box and click delete

Product Page: DSL-2750U Firmware Version: ME_1.04

D-Link

DSL-2750U //

SETUP ADVANCED MAINTENANCE STATUS HELP

Wizard

Internet Setup

Wireless Connection

3G

Failover

Local Network

IPv6 Local Network

Time and Date

Logout

INTERNET SETUP

ATM Interface Setup
Choose "Add", "Edit", or "Delete" to configure WAN interface. A maximum of 8 entries can be configured.

If you want to change WAN services type, Please select ETH or DSL

WAN Services type: ETH WAN DSL

WAN SETUP

	VPI/VCI	VLAN Mux	Service Name	Protocol	IGMP	NAT	IPv6	Status	Action
<input checked="" type="checkbox"/>	8/35	-1	pppoe_0_8_35	PPPoE	Disabled	Enabled	Disabled	Unconfigured	

After deleting the profile, click on the add button

For the correct VPI/VCI settings, please contact your ISP (internet service provider)

INTERNET SETUP
Wide Area Network (WAN) Service Setup

ATM PVC CONFIGURATION
VPI: (0-255)
VCI: (32-65535)
Service Category:
Peak Cell Rate: (cells/s)
Sustainable Cell Rate: (cells/s)
Maximum Burst Size: (cells)

IP QOS SCHEDULER ALGORITHM
 Weighted Round Robin
 Weighted Fair Queuing
Default Queue Weight: [1-63]
Default Queue Precedence: [1-8]
VC WRR Weight: [1-63]
VC Precedence: [1-8]

Enter the following details:

- Select PPPoE (PPP over Ethernet) connection
- Select LLC/Snap bridging
- Inset your username/Password which is provided by your Service Provider (ISP)
- MTU -1492 (please also confirm this number with your ISP)
- Enable firewall
- Enable NAT
- Click next

CONNECTION TYPE

Protocol: PPP over Ethernet (PPPoE) ▾

Encapsulation Mode: LLC/SNAP-BRIDGING ▾

Enable Multiple Vlan Over One Connection:

802.1P Priority [0-7]: -1

802.1Q VLAN ID [0-4094]: -1

PPP USERNAME AND PASSWORD

PPP Username: guest@telkomadsl

PPP Password: •••••

Confirm PPP Password: •••••

Authentication Method: AUTO ▾

Dial On Demand (With Idle Timeout Timer):

Inactivity Timeout: (minutes [1-4320])

Dial On Manual:

PPPoE pass-through:

MTU Size: 1492 (576-1492)

NETWORK ADDRESS TRANSLATION SETTINGS

Enable NAT:

Enable Firewall:

Enable IGMP Multicast:

Enable MLD Proxy:

Service Name: pppoe_0_8_35

Next Cancel

In the summary page to follow, please double check your details, then click Apply

Product Page: DSL-2750U Firmware Version: ME_1.04

D-Link

DSL-2750U // SETUP ADVANCED MAINTENANCE STATUS HELP

Wizard

Internet Setup

Wireless Connection

3G

Failover

Local Network

IPv6 Local Network

Time and Date

Logout

WAN

Make sure that the settings below match the settings provided by your ISP.

Click "Apply" to save these settings. Click "Back" to make any modifications.
NOTE: You need to reboot to activate this WAN interface and further configure services over this interface.

SETUP - SUMMARY

PVC / VPI / VCI :	0 / 8 / 35
Connection Type:	PPPoE
Service Name:	pppoe_0_8_35
Service Category:	UBR
IP Address:	Automatically Assigned
Service State:	Enabled
NAT:	Enabled
Firewall:	Enabled
IGMP Multicast:	Disabled
Quality Of Service:	Enabled

Helpful Hints...

When configuring the router to access the Internet, be sure to choose the correct **Connection Type** from the list below.

Please take care when entering your **username** and **password** as these are case sensitive. The majority of connection issues are caused by incorrect **username** or **password** combinations.

Note: Be sure to restart the router for the new Internet Setting to take effect.

[More...](#)

Once you have followed these details, your DSL-2750U will be configured for internet access
(Please note in some instances the router will take between 1-7 minutes to connect to the internet after these steps have been followed)