



Configuration examples for the D-Link NetDefend Firewall series

DFL-210/800/1600/2500

Scenario: Configure lan-to-lan tunnels between
a main office and two remote offices
(sometimes called Hub and Spoke)

Last update: 2007-01-18

Overview

In this document, the notation *Objects->Address book* means that in the tree on the left side of the screen **Objects** first should be clicked (expanded) and then **Address Book**.

Most of the examples in this document are adapted for the DFL-800. The same settings can easily be used for all other models in the series. The only difference is the names of the interfaces. Since the DFL-1600 and DFL-2500 has more than one lan interface, the lan interfaces are named lan1, lan2 and lan3 not just lan.


The screenshots in this document is from firmware version 2.11.02. If you are using an earlier version of the firmware, the screenshots may not be identical to what you see on your browser.

To prevent existing settings to interfere with the settings in these guides, reset the firewall to factory defaults before starting.

Configure lan-to-lan tunnels between a main office and two remote offices (sometimes called Hub and Spoke).

This guide shows how to configure tunnels between three firewalls. First create one tunnel from firewall A to firewall B and then a second tunnel from firewall A to firewall C. Users behind firewall B should be able to reach resources behind firewall C (and the other way around).

- a IP: 192.168.3.1/24
- b IP: 192.168.110.5/24
- c IP: 192.168.110.1/24
- d IP: 192.168.110.3/24
- e IP: 192.168.1.1/24
- f IP: 192.168.2.2/24



1. Firewall A - Addresses

Go to *Objects* -> *Address book* -> *InterfaceAddresses*.

Edit the following items:

Change **lan_ip** to **192.168.3.1**

Change **lannet** to **192.168.3.0/24**

Change **wan1_ip** to **192.168.110.5**

Change **wan1net** to **192.168.110.0/24**

Go to *Objects* -> *Address book*.

Add a new Address Folder called **RemoteHosts**.

In the new folder, add a new IP address:

Name: **fwB-net**

IP Address: **192.168.1.0/24**

Click Ok

Add a new IP address:

Name: **fwB**

IP Address: **192.168.110.1**

Click Ok

Add a new IP address:

Name: **fwC-net**

IP Address: **192.168.2.0/24**

Click Ok

Add a new IP address:

Name: **fwC-remotegw**

IP Address: **192.168.110.3**

Click Ok

Add a new IP4 Group:

Name:


Group members: Available Selected

lan_ip	>>	lannet
dmz_ip		fwC-net
dmznet	<<	
wan1_ip		
wan1net		
wan2_ip		

Name: **tunnelAB-localnet**

Add **lannet** and **fwC-net** to the Group members

Click Ok



Add a new IP4 Group:

Name: **tunnelAC-localnet**

Add **lanet** and **fwB-net** to the Group members


Click Ok

2. Firewall A - Pre-shared keys

Go to *Objects* -> *Authentication Objects*.

Add a new Pre-Shared Key.

General:



The screenshot shows the 'General' tab of a configuration window. At the top, there is a 'General' header with a plus icon. Below it, a key icon is followed by the text: 'PSK (Pre-Shared Key) authentication is based on a shared secret that is known only by the parties involved'. Underneath, the 'Name:' label is followed by a text input field containing the value 'fwABC-psk'.

Name: **fwABC-psk**

Shared Secret:



The screenshot shows the 'Shared Secret' tab of a configuration window. At the top, there is a radio button selected next to the label 'Passphrase'. Below this, there are two text input fields. The first is labeled 'Shared Secret:' and contains ten asterisks. The second is labeled 'Confirm Secret:' and also contains ten asterisks.

Select **Passphrase** and enter a shared secret.

Click Ok.

3. Firewall A - IPsec tunnel interface

Go to *Interfaces* -> *IPsec*.

Add a new IPsec Tunnel.

In the General tab:

General:

Name:	<input type="text" value="ipsectunnelAB"/>
Local Network:	<input type="text" value="tunnelAB-localnet"/> ▼
Remote Network:	<input type="text" value="fwB-net"/> ▼
Remote Endpoint:	<input type="text" value="fwB"/> ▼
Encapsulation Mode:	<input type="text" value="Tunnel"/> ▼

Name: **ipsectunnelAB**
Local Network: **tunnelAB-localnet**
Remote Network: **fwB-net**
Remote Endpoint: **fwB**
Encapsulation Mode: **Tunnel**

Algorithms:

IKE Algorithms:	<input type="text" value="High"/> ▼
IKE Life Time	<input type="text" value="28800"/> seconds
IPsec Algorithms:	<input type="text" value="High"/> ▼
IPsec Life Time	<input type="text" value="3600"/> seconds
IPsec Life Time	<input type="text" value="0"/> kilobytes

IKE Algorithms: **High**
IKE Life Time: **28800**
IPsec Algorithms: **High**
IPsec Life Time: **3600**
IPsec Life Time: **0**

In the Authentication tab:

Authentication:

<input checked="" type="radio"/> Pre-Shared Key	
Pre-Shared Key:	<input type="text" value="fwABC-psk"/> ▼

Enable **Pre-Shared Key** and select **fwABC-psk** from the dropdown list.

Click Ok.

Add a new IPsec Tunnel.

In the General tab:

General:

Name:	<input type="text" value="ipsectunnelAC"/>
Local Network:	<input type="text" value="tunnelAC-localnet"/> ▼
Remote Network:	<input type="text" value="fwC-net"/> ▼
Remote Endpoint:	<input type="text" value="fwC"/> ▼
Encapsulation Mode:	<input type="text" value="Tunnel"/> ▼

Name: **ipsectunnelAC**
Local Network: **tunnelAC-localnet**
Remote Network: **fwC-net**
Remote Endpoint: **fwC**
Encapsulation Mode: **Tunnel**

Algorithms:

IKE Algorithms:	<input type="text" value="High"/> ▼
IKE Life Time	<input type="text" value="28800"/> seconds
IPsec Algorithms:	<input type="text" value="High"/> ▼
IPsec Life Time	<input type="text" value="3600"/> seconds
IPsec Life Time	<input type="text" value="0"/> kilobytes

IKE Algorithms: **High**
IKE Life Time: **28800**
IPsec Algorithms: **High**
IPsec Life Time: **3600**
IPsec Life Time: **0**

In the Authentication tab:

<input checked="" type="radio"/> Pre-Shared Key
Pre-Shared Key: <input type="text" value="fwABC-psk"/> ▼

Authentication:

Enable **Pre-Shared Key** and select **fwABC-psk** from the dropdown list.

Click Ok.

4. Firewall A - Rules

Go to *Rules* -> *IP Rules*.

Create a new IP Rule Folder called **lan_to_fwBC**.

In the new folder, add a new IP Rule.

In the General tab:

General:

Name:	<input type="text" value="allow_all"/>
Action:	<input type="text" value="Allow"/> ▼
Service:	<input type="text" value="all_services"/> ▼
Schedule:	<input type="text" value="(None)"/> ▼

Name: **allow_all**

Action: **Allow**

Service: **all_services**

Address Filter:

	Source	Destination
Interface:	<input type="text" value="lan"/> ▼	<input type="text" value="ipsectunnelAB"/> ▼
Network:	<input type="text" value="lannet"/> ▼	<input type="text" value="fwB-net"/> ▼

Source Interface: **lan**

Source Network: **lannet**

Destination Interface: **ipsectunnelAB**

Destination Network: **fwB-net**

Click Ok.

Add a new IP Rule.

In the General tab:

General:

Name: **allow_all**

Action: **Allow**

Service: **all_services**

Address Filter:

	Source	Destination
Interface:	<input type="text" value="ipsectunnelAC"/> ▼	<input type="text" value="ipsectunnelAB"/> ▼
Network:	<input type="text" value="fwC-net"/> ▼	<input type="text" value="fwB-net"/> ▼

Source Interface: **ipsectunnelAC**
Source Network: **fwC-net**
Destination Interface: **ipsectunnelAB**
Destination Network: **fwB-net**

Click Ok.

Add a new IP Rule.

In the General tab:

General:

Name: **allow_all**
Action: **Allow**
Service: **all_services**

Address Filter:

Source Interface: **ipsectunnelAB**
Source Network: **fwB-net**
Destination Interface: **lan**
Destination Network: **lannet**

Click Ok.

Add a new IP Rule.

In the General tab:

General:

Name: **allow_all**
Action: **Allow**
Service: **all_services**

Address Filter:

Source Interface: **ipsectunnelAB**
Source Network: **fwB-net**
Destination Interface: **ipsectunnelAC**
Destination Network: **fwC-net**

Click Ok.

Add a new IP Rule.

In the General tab:

General:

Name: **allow_all**

Action: **Allow**

Service: **all_services**

Address Filter:

Source Interface: **ipsectunnelAC**

Source Network: **fwC-net**

Destination Interface: **lan**

Destination Network: **lannet**

Click Ok.

Add a new IP Rule.

In the General tab:

General:

Name: **allow_all**

Action: **Allow**

Service: **all_services**

Address Filter:

Source Interface: **lan**

Source Network: **lannet**

Destination Interface: **ipsectunnelAC**

Destination Network: **fwC-net**

Click Ok.

Save and activate the configuration on firewall A.

5. Firewall B - Addresses

Go to *Objects -> Address book -> InterfaceAddresses*.

Edit the following items:

Change **lan_ip** to **192.168.1.1**

Change **lannet** to **192.168.1.0/24**

Change **wan1_ip** to **192.168.110.1**

Change **wan1net** to **192.168.110.0/24**

Go to *Objects -> Address book*.

Add a new Address Folder called **RemoteHosts**.

In the new folder, add a new IP address:

Name: **fwA-net**

IP Address: **192.168.3.0/24**

Click Ok

Add a new IP address:

Name: **fwA**

IP Address: **192.168.110.5**

Click Ok

Add a new IP address:

Name: **fwC-net**

IP Address: **192.168.2.0/24**

Click Ok

Add a new IP4 Group:

Name: **fwB-remotenets**

Add **fwA-net** and **fwC-net** to the Group members

Click Ok

6. Firewall B - Pre-shared keys

Follow the instructions in step 2 to add a pre-shared key called fwABC-psk to firewall B. The passphrase has to be the same as the passphrase on firewall A.

7. Firewall B - IPsec tunnel interface

Go to *Interfaces* -> *IPsec*.

Add a new IPsec Tunnel.

In the *General* tab:

General:

Name:	<input type="text" value="ipsectunnelBA"/>
Local Network:	<input type="text" value="lannet"/> ▼
Remote Network:	<input type="text" value="fwB-remotenets"/> ▼
Remote Endpoint:	<input type="text" value="fwA"/> ▼
Encapsulation Mode:	<input type="text" value="Tunnel"/> ▼

Name: **ipsectunnelBA**
Local Network: **lannet**
Remote Network: **fwB-remotenets**
Remote Endpoint: **fwA**
Encapsulation Mode: **Tunnel**

Algorithms:

IKE Algorithms:	<input type="text" value="High"/> ▼
IKE Life Time	<input type="text" value="28800"/> seconds
IPsec Algorithms:	<input type="text" value="High"/> ▼
IPsec Life Time	<input type="text" value="3600"/> seconds
IPsec Life Time	<input type="text" value="0"/> kilobytes

IKE Algorithms: **High**
IKE Life Time: **28800**
IPsec Algorithms: **High**
IPsec Life Time: **3600**
IPsec Life Time: **0**

In the Authentication tab:

Authentication:

<input checked="" type="radio"/> Pre-Shared Key	
Pre-Shared Key:	<input type="text" value="fwABC-psk"/> ▼

Enable **Pre-Shared Key** and select **fwABC-psk** from the dropdown list.

Click Ok.

8. Firewall B - Rules

Go to *Rules* -> *IP Rules*.

Create a new IP Rule Folder called **lan_to_fwA**.

In the new folder, add a new IP Rule.

In the General tab:

General:

Name:	<input type="text" value="allow_all"/>
Action:	<input type="text" value="Allow"/> ▼
Service:	<input type="text" value="all_services"/> ▼
Schedule:	<input type="text" value="(None)"/> ▼

Name: **allow_all**

Action: **Allow**

Service: **all_services**

Address Filter:

	Source	Destination
Interface:	<input type="text" value="lan"/> ▼	<input type="text" value="ipsectunnelBA"/> ▼
Network:	<input type="text" value="lannet"/> ▼	<input type="text" value="fwB-remotenets"/> ▼

Source Interface: **lan**

Source Network: **lannet**

Destination Interface: **ipsectunnelBA**

Destination Network: **fwB-remotenets**

Click Ok.

Add a new IP Rule.

In the General tab:

General:

Name: **allow_all**

Action: **Allow**

Service: **all_services**

Address Filter:

	Source	Destination
Interface:	<input type="text" value="ipsectunnelBA"/>	<input type="text" value="lan"/>
Network:	<input type="text" value="fwB-remotenets"/>	<input type="text" value="lannet"/>

Source Interface: **ipsectunnelBA**

Source Network: **fwB-remotenets**

Destination Interface: **lan**

Destination Network: **lannet**

Click Ok.

Save and activate the configuration on firewall B.

9. Firewall C - Addresses

Go to *Objects* -> *Address book* -> *InterfaceAddresses*.

Edit the following items:

Change **lan_ip** to **192.168.2.1**

Change **lannet** to **192.168.2.0/24**

Change **wan1_ip** to **192.168.110.3**

Change **wan1net** to **192.168.110.0/24**

Go to *Objects* -> *Address book*.

Add a new Address Folder called **RemoteHosts**.

In the new folder, add a new IP address:

Name: **fwA-net**

IP Address: **192.168.3.0/24**

Click Ok

Add a new IP address:

Name: **fwA**

IP Address: **192.168.110.5**

Click Ok

Add a new IP address:

Name: **fwB-net**

IP Address: **192.168.1.0/24**

Click Ok

Add a new IP4 Group:

Name: **fwC-remotenets**

Add **fwA-net** and **fwB-net** to the Group members

Click Ok

10. Firewall C - Pre-shared keys

Follow the instructions in step 2 to add a pre-shared key called fwABC-psk to firewall C. The passphrase has to be the same as the passphrase on firewall A.

11. Firewall C - IPsec interfaces

Go to *Interfaces* -> *IPsec*.

Add a new IPsec Tunnel.

In the General tab:

General:

Name:	<input type="text" value="ipsectunnelCA"/>
Local Network:	<input type="text" value="lannet"/> ▼
Remote Network:	<input type="text" value="fwC-remotenets"/> ▼
Remote Endpoint:	<input type="text" value="fwA"/> ▼
Encapsulation Mode:	<input type="text" value="Tunnel"/> ▼

Name: **ipsectunnelCA**

Local Network: **lannet**

Remote Network: **fwC-remotenets**

Remote Endpoint: **fwA**

Encapsulation Mode: **Tunnel**

Algorithms:

IKE Algorithms:	<input type="text" value="High"/> ▼
IKE Life Time	<input type="text" value="28800"/> seconds
IPsec Algorithms:	<input type="text" value="High"/> ▼
IPsec Life Time	<input type="text" value="3600"/> seconds
IPsec Life Time	<input type="text" value="0"/> kilobytes

IKE Algorithms: **High**

IKE Life Time: **28800**

IPsec Algorithms: **High**

IPsec Life Time: **3600**

IPsec Life Time: **0**

In the Authentication tab:

Authentication:



Pre-Shared Key
Pre-Shared Key: fwABC-psk

Enable **Pre-Shared Key** and select **fwABC-psk** from the dropdown list.

Click Ok.

12. Firewall C - Rules

Go to *Rules* -> *IP Rules*.

Create a new IP Rule Folder called **lan_to_fwA**.

In the new folder, add a new IP Rule.

In the General tab:

General:

Name: **allow_all**

Action: **Allow**

Service: **all_services**

Address Filter:

Source Interface: **lan**

Source Network: **lanet**

Destination Interface: **ipsectunnelCA**

Destination Network: **fwC-remotenets**

Click Ok.

Add a new IP Rule.

In the General tab:

General:

Name: **allow_all**

Action: **Allow**

Service: **all_services**

Address Filter:

Source Interface: **ipsectunnelCA**

Source Network: **fwC-remotenets**

Destination Interface: **lan**

Destination Network: **lannet**

Click Ok.

Save and activate the configuration on firewall C.